

SEMICONDUCTOR COMPONENT

Cross-Reference to Related Application:

This application is a continuation of copending International
5 Application No. PCT/DE00/01251, filed April 20, 2000, which
designated the United States.

Background of the Invention:

Field of the Invention:

The invention relates to a voltage-controlled semiconductor
10 component in which a high voltage is present between the
terminals forming the load path.

The costs in the manufacture of a grid power supply constitute
a fundamental problem. Suitable selection of a grid power
supply is dependent on the application, just like the
15 components that are intended to be used. Switched-mode grid
power supplies, in particular, are being used more and more
often. This is due, *inter alia*, to the fact that many complex
circuit configuration of a switched-mode power supply can be
combined on a single integrated semiconductor chip. This
20 enables cost-effective manufacture. A semiconductor chip of
this type has, in particular, a power switching device and a
drive configuration for the power switching device. In this
case, the load terminals of the power switching device are

connected to a high supply voltage, whereas a voltage having a significantly lower signal level is required for driving the power switching device. Therefore, the integrated semiconductor chip has regions that are configured for a high-voltage application (power switching device) and further regions that work with a low voltage level (drive configuration). Therefore, a semiconductor chip of this type requires a terminal to which a high supply potential can be applied, and also a further terminal that makes available a low supply potential for the control components. The low supply potential can be generated for example by reducing the high supply potential via a resistor between the further terminal and the high supply potential. However, wiring of this type causes permanent losses.

Therefore, it would be advantageous if a signal that is fed to a drive configuration and would serve for its supply could be derived directly from the load voltage present across the power-switching device. At the same time, the power-switching device should assume the lowest possible forward resistance in the conducting state.

A power-switching device of this type is disclosed, for example, in Balakrishnan (U.S. Patent No. 5,285,369), which describes an integrated circuit configuration used in a switched-mode power supply. In this case, the integrated circuit configuration has a power-switching device including

two semiconductor switches connected in series with one another. The first semiconductor switch is a JFET, while the second semiconductor switch is a high-voltage MOSFET. At the junction point between the two semiconductor switches, which are connected up in series by their load paths, a low voltage can be tapped off, which is fed to a voltage regulator of the drive device. As a result, components having a high and having a low supply potential requirement in the integrated circuit configuration can be combined because a signal derived from the load voltage can be fed to the components having a low supply potential. The construction of the power-switching device including a JFET and a high-voltage MOSFET is described for example in Eklund (U.S. Patent No. 4,811,075) or Eklund (U.S. Patent No. 5,313,082).

However, disadvantages with such power switching devices (hereinafter, "semiconductor component") include the complex fabrication method requiring very many mask steps to fabricate the complicated layer sequence and the different doping thereof.

Summary of the Invention:

It is accordingly an object of the invention to provide a semiconductor component that overcomes the hereinafore-mentioned disadvantages of the heretofore-known devices of this general type and that derives a signal from a high load voltage; this signal can be used directly for driving the

semiconductor component or, alternatively, a control device. A further object is to fabricate the semiconductor component in a simple manner.

With the foregoing and other objects in view, there is
5 provided, in accordance with the invention, a semiconductor component. The semiconductor component can be vertical or lateral. The semiconductor component includes a substrate, a more highly doped layer, a multiplicity of MOS cells, a first well, a first source region, a first gate, a plurality of
10 further MOS cells, and at least one region of the second conductivity type. The substrate of a first conductivity type has a first and a second side covered by an insulating layer on the first side. The more highly doped layer of the first conductivity type is applied on the second side. The metallic
15 drain contact is applied on the more highly doped layer. The multiplicity of MOS cells on the first side of the substrate is for forming a first semiconductor switch. Each MOS cell has a first well of the second conductivity type, the first well being introduced into the substrate and reaching the
20 first side; a first source region of the first conductivity type is incorporated into the well, reaches to the first side of the substrate, and connects to a first metallic source contact extending through the insulating layer. A first gate is on the side of the insulating layer that is remote from the
25 substrate. The gate partly covers the well and connects to a metallic gate contact. A plurality of further MOS cells

constructed like the multiplicity of MOS cells has a second well, a second source region, and a second gate on the first side of the substrate for forming a second semiconductor switch; the second source regions of the further MOS cells connect to a second source contact on the first side. The source contact is electrically insulated from the first source contact and extends through the insulating layer. A region of the second conductivity type is incorporated into the substrate, reaches to the first side, and electrically connects to the second gate of the further MOS cells. The potential of the region floats relative to the potential of the first and second source regions of the MOS cells and further MOS cells.

The basic construction and the method of operation are explained below. The semiconductor component is configured, in particular, as a MOSFET or IGBT. In practice, a semiconductor component of this type includes a multiplicity of MOS cells that are connected in parallel and are introduced on a first side of a substrate of the first conductivity type. The load voltage is present between a source contact and a drain contact. The voltage present at a gate sets the magnitude of the current between the source contact and the drain contact. The MOS cells connected in parallel form the "active cell array" of the semiconductor component and have a first source contact. This cell array forms a first semiconductor switch.

A region of some MOS cells is provided with a dedicated, second source contact to derive a signal having a significantly lower voltage from the load voltage between the source contact and drain contact, according to the invention, in the active cell array of the semiconductor component. This means nothing more than that the first metallic source contact, which is connected to the source regions of the MOS cells forming the active cell array, is interrupted.

Furthermore, in the case of the further MOS cells (disconnected MOS cells), the gate contacts are electrically isolated from the first gate contacts of the MOS cells facing the cell array. These cells then form a second semiconductor switch that shares its drain with the drain of the first semiconductor switch. The cells of the second semiconductor switch are hereinafter called "start-up cells". The gate of the start-up cells is readable and can be conductively connected to a likewise separately metallized "source region" of further adjacent cells. These source regions of the second conductivity type form, with the substrate and at least one well of the start-up cells, which are likewise of the second conductivity type, at least one parasitic transistor, which are hereinafter called "gate-drive cell". These cells have a drain terminal shared with the first and second semiconductor switches.

The potential of the "source regions" floats relative to the source potential of the start-up cells and relative to the

source potential of the MOS cells of the semiconductor component that belong to the active cell array. If the source potential of the start-up cells is capacitively coupled to the source potential of the MOS cells of the active cell array of the semiconductor component, then it is the case that, due to this capacitive coupling, in the event of a rising drain-source voltage across the active cell array, the voltage between the source region of the start-up cells and the drain region of the semiconductor component also rises. All the cells of the semiconductor component share the drain region of the active cell array. As a result of the capacitive coupling, a space charge zone that extends both vertically and laterally forms around the well surrounding the source region of the start-up cells. As soon as the space charge zone reaches the adjacent "source region", these are coupled in terms of potential. The voltage at which the space charge zone reaches the adjacent source regions of the gate-drive cells is hereinafter called "punch-through voltage". In this case, the punch-through voltage can be set by the doping of the substrate at the surface and by the distance between the source region and the start-up cells. It is ideally set to a value distinctly above the threshold voltage of the start-up cell, but below the maximum specification limit thereof: a value of twelve volts (12 V) being customary in high-voltage power technology. This voltage cannot be exceeded even in the event of very high drain-source voltage differences of the MOS cells of the active cell array. This is of great importance

particularly in the event of very rapid du/dt peaks in the load circuit because the gate voltage of the start-up cells is intended to be switched by the potential of the source regions. This natural limiting of the voltage occurring at the source regions achieves perfect protection of the gate oxide of the start-up cells. The voltage to be applied by the start-up cells typically lies between ten and fifteen volts (10 - 15 V). This voltage is sufficient for operating a control device (for example a control IC) and for directly driving the first gate of the MOS cells of the active cell array.

Furthermore, the semiconductor component according to the invention has the advantage that even negative supply potentials between the source and drain contacts of the active cell array do not lead to destruction of the start-up cells or gate-drive cells (i.e. of the source region). In this case, the "body diode" formed between the well with respect to the substrate of the start-up cells or source regions functions as a protective element. Therefore, no voltage difference of more than -1 V with respect to the drain region can occur at the gate of the start-up cells. By contrast, the potential difference of the second gate of the start-up cells relative to the source potential of the start-up cells can assume large values if the voltage of the start-up cells is buffered by an external charge store and is not limited. Therefore, external voltage limiting with a zener diode, for example, is

advantageous when using the semiconductor component according to the invention. In practice, however, there is no restriction on use because, in the standard power technologies used, the gate oxide can be continuously loaded up to twenty 5 volts (< 20 V) and momentarily loaded up to fifty volts (< 50 V).

In one preferred configuration of the MOS cells, the gate-drive cells, or source regions of the second conductivity type, are surrounded exclusively by the start-up cells. Together, they form a structure that switches on the MOS cells of the active cell array.

As an alternative, at least one start-up cell can be surrounded exclusively by gate-drive cells (or source regions of the second conductivity type). The resulting structure 15 switches on the MOS cells of the active cell array.

This structure that switches on the active cell array can advantageously be configured adjacent the MOS cells of the active cell array or be completely surrounded by the MOS cells of the active cell array. This configuration produces a 20 signal having, in comparison, a significantly lower voltage generated from the voltage present between the drain and source contacts of the active cell array. This signal can be used for driving either the first gate of the semiconductor component or, alternatively, a control IC.

A lateral insulation is advantageously provided between the MOS cells of the active cell array and the structure that switches on these cells, in order to avoid parasitic effects.

In a further advantageous refinement, the source region of the gate-drive cell is disposed near the drain electrode holding the charge. Then, by virtue of the propagation of a space charge zone between the MOS cells of the start-up cell and the source region of the gate-drive cell, the gate can drive the start-up cell in all cases. The source region of the gate-drive cells is adapted to the punch-through voltage in the event of a threshold voltage being exceeded in the load circuit of the semiconductor component, which threshold voltage can be predetermined by the configuration of the source region.

A minimal power is required for driving the second gate of the start-up cell, since MOS gates require a minimal gate charge on account of their capacitive coupling to the substrate.

This minimal charge has to be accumulated during the propagation of the space charge zone from the source region of the gate-drive cell. At the same time, the potential of the source regions of the gate-drive cell must be higher than the source potential of the start-up cell at least by the magnitude of the threshold voltage of the start-up cell.

Therefore, a charge carrier reservoir connected to the source region of the gate-drive cell must be present.

This merely means that the source region of the gate-drive cell must be configured in such a way as to enable effective accumulation of the charge by the gate-drive cell through the formation of an electric field. Therefore, the source region of the gate-drive cell is configured in such a way that the latter is completely depleted in the event of propagation of the space charge zone between the source region of the start-up cell and the drain region. The local electric field generated by this region relative to the substrate must be high enough that the depletion charge flows into the source region of the gate-drive cell, and charges the latter further, even in the event of a positive potential of the source region of the gate-drive cell relative to the potential of the start-up cells or the potential of the wells of the second conductivity type of the MOS cells of the active cell array. The configuration of such a region, a buried region, is known from "compensation components". These regions can advantageously be fabricated in a simple manner without a further additional mask relative to a standard process in the case of compensation components. The fabrication method is described for example in German Patent DE 198 40 032, corresponding to International Publication WO 00/14807, which was not published before the priority date. In the case of a semiconductor component of vertical construction, therefore, the source region is advantageously extended orthogonally with respect to the main sides of the first substrate in the direction of the drain region.

In an advantageous refinement, the wells of the second conductivity type of the MOS cells and of the start-up cells may likewise be formed orthogonally with respect to a main side of the semiconductor component in the direction of the drain electrode. The advantages are that a high avalanche strength and a large current-carrying capacity before or during breakdown are made possible as a result in the active cell array of the semiconductor component.

In the case of a semiconductor component of lateral construction, the source region of the gate-drive cells is advantageously formed parallel to the main sides of the substrate in the direction of the drain region. In this case, the source region of the gate-drive cells may run along the top side in the substrate of the semiconductor component.

The source region of the gate-drive cell is dimensioned in such a way that the charge of this region suffices to charge, at least to the threshold voltage of the start-up cells, the gate to be switched of all the start-up cells whose gates are connected to the source region of the gate-drive cells. In this case, dimensioning can be understood to mean both the spatial configuration and the doping of the source region. Since parasitic capacitances and leakage currents occur in practice, dimensioning with which, for example, the gate of two start-up cells can be charged by a gate-drive cell is advantageous. Depending on the configuration of the source

region of the gate-drive cell, it may be necessary to use a plurality of gate-drive cells for driving a start-up cell.

In order to prevent unintentional latching in the source region, the source region preferably is without a region of the first conductivity type. Consequently, a switch-on of a parasitic bipolar structure in the source region is prevented even in the event of a high hole current. The customary implantation during the fabrication of a conventional MOS cell should therefore be shaded at the locations of the gate-drive cells via phototechnology.

Because the start-up cells supply a permanent charging current even when a high drain-source voltage of the active cell array is present, they must be both short-circuit-proof and thermostable. In order to obtain the short-circuit strength, partial shading of the channel terminal implantation should advantageously be performed. A procedure of this type is described for example in commonly owned German Patent DE 198 08 348 C1, corresponding to U.S. Patent No. 6,271,562.

In a further advantageous refinement, the source regions are laterally insulated from the start-up cells in order to form "surge detection cells". The surge detection cells are configured in such a way that the breakdown voltage of these cells lies below the value of the breakdown voltage of the MOS cells of the active cell array. The source regions of the

surge detection cells can therefore reach into the substrate to a lesser extent than the wells of the second conductivity type of the MOS cells of the active cell array. These regions are advantageously provided for contact-connection with a resistor. Overvoltage detection is achieved in a simple manner as a result. As an alternative or in addition, the doping of the surge detection cell can be chosen in such a way that its breakdown voltage has a lower value than the breakdown voltage of the MOS cells of the active cell array, e.g. by increasing the doping of the p-type region below the p-type well. As soon as the drain-source voltage of the semiconductor component exceeds the breakdown voltage of the surge detection cell, a current that raises the potential of the cell flows in the cell. This voltage rise can then be detected (i.e. with a resistor) and used as a trigger of suitable protective measures, for example, with a control IC. It would also be conceivable for the gate of the MOS cells of the active cell arrays to be driven directly, and protected, with a suitable metallization. The variation of the breakdown voltage can be achieved most simply by the source regions of the surge detection cell reaching into the substrate to a lesser extent than the wells of the second conductivity type of the MOS cells of the active cell array. The fabrication process known from the compensation elements can then advantageously be used or varied.

Consequently, the advantage of the surge detection cell is that active zener protection that is completely independent of external circuit measures can be realized in a simple manner. The potential rise of the surge detection cell can be used
5 directly for switching on the first gate of the MOS cells of the active cell array via a plurality of start-up cells. As a result, the drain-source voltage of the semiconductor component and, correspondingly, the potential of the surge detection cell decrease. Consequently, a stable situation is established in which a first gate voltage different from zero
10 volts (0 V) is present and wherein a drain-source voltage above the breakdown voltage of the surge detection cell but below the breakdown voltage of the main transistor is established. The semiconductor component is thus protected and cannot attain avalanche.
15

When wiring with an external resistor, the first gate is switched on only when the breakdown voltage of the surge detection cell is exceeded. However, if the threshold voltage is exceeded in the region of the punch-through voltage of the
20 surge detection/start-up cell array, the first gate of the semiconductor component remains switched off. In order to protect the surge detection cell, the external resistor must be dimensioned in such a way that, in the case of a maximum current-carrying capacity of the surge detection cell, the
25 drain potential exceeds the breakdown voltage of the main transistor. Seen figuratively, the approximately rectangular

breakdown characteristic curve of the active cell array is consequently initially intersected with a resistance straight line. In an advantageous manner, the surge detection cell is laterally insulated in such a way that the voltage rise of the source region of the surge detection cell leads neither to the switching-on of the body diode with respect to the substrate nor to breakdown with respect to adjacent cells that are at the source potential. Suitable edge structures are described for example in German Published, Non-prosecuted Patent Application DE 197 48 524 A1.

The dimensioning of the self-switching-on structure, including start-up cells and parasitic gate-drive cells, can advantageously be facilitated by cascading a plurality of stages of gate-drive cells and start-up cells, respectively. Thus, a plurality of gate-drive cells can switch on, for example, ten start-up cells. Therefore, the charging current thereof is used to switch on a further thousand (1,000) start-up cells. The current of these cells can then be utilized for rapidly switching on a large-area active cell array.

If the drain-source voltage falls below the value of the externally buffered source potential of the start-up cells, the charging current of the start-up cells is extinguished. This makes it possible to realize, for example, voltage zero-point identification or a status signal.

For renewed switching-on of the start-up cells, it is then necessary to renew the buried charge in the source region of the gate-drive cell. Because the potential of the source regions of the gate-drive cell floats, this cannot be done by diffusion of holes from the source region itself, since no current can subsequently be supplied externally. However, the required charge can be provided by injection of holes from the source region of the start-up cells. For this purpose, the source region in the start-up cells must be connected to a small capacitor, so that the potential of the well of the second conductivity type of the start-up cells is held at a positive voltage. As soon as the drain-source voltage of the start-up cell falls below this potential, the body diode injects holes. Consequently, an existing space charge zone below the gate-drive cell is reduced very rapidly since the depleted source regions are reverse-biased with respect to the substrate and thus represent the most negative potential for the injected holes in the vicinity. The source region of the gate-drive cell is thus flooded with holes and is thus again available for a repeated switch-on cycle.

The semiconductor component according to the invention can be used both for n-channel transistors and for p-channel transistors. If the semiconductor component is embodied as an IGBT, a reset structure is not required since the holes can be injected via a rear-side emitter. In the event of a large injection of charge carriers, however, the potential of the

gate-drive cell can rise far in excess of the potential of the start-up cell, whereby there is the risk of destruction of the gate oxide. This can be reduced by limiting the voltage between the start-up cell and the source region of the gate-drive cell.

Other features which are considered as characteristic for the invention are set forth in the appended claims.

Although the invention is illustrated and described herein as embodied in a semiconductor component, it is nevertheless not intended to be limited to the details shown, since various modifications and structural changes may be made therein without departing from the spirit of the invention and within the scope and range of equivalents of the claims.

The construction and method of operation of the invention, however, together with additional objects and advantages thereof will be best understood from the following description of specific embodiments when read in connection with the accompanying drawings.

Brief Description of the Drawings:

Fig. 1 is a simplified, schematic diagram of a semiconductor component according to the invention;

Fig. 2 is a cross-sectional view through part of a vertical semiconductor component;

Fig. 3 is a plan view of the vertical semiconductor component according to the invention;

5 Fig. 4 is a schematic diagram of a further embodiment of the semiconductor component showing the physical method of operation;

Fig. 5 is a schematic diagram of a further embodiment of the semiconductor component showing the principle of cascading;

10 Fig. 6 is a plan view showing a basic cell configuration and the electrical wiring thereof for cascading; and

Fig. 7 is a cross-sectional view through a lateral semiconductor component according to the invention.

Description of the Preferred Embodiments:

15 Referring now to the figures of the drawings in detail and first, particularly to Fig. 1 thereof, there is shown a simple electrical equivalent circuit diagram of a semiconductor component 20 according to the invention. The semiconductor component 20 has an n-channel MOSFET M formed from a
20 multiplicity of MOS cells that are connected in parallel and represent the active cell array of the semiconductor component

20. A drain terminal D and a source terminal S form the two load terminals of the semiconductor component 20. A high voltage, which might be in the region of several hundred volts, for example, is present at the load terminals D, S.

5 Moreover, a further n-channel MOSFET SU is provided, which is connected by its drain terminal to the drain terminal D of the MOSFET M. A parasitic transistor GD is connected by its drain terminal likewise to the drain terminal D of the MOSFET M. Its gate terminal is connected firstly to the gate terminal of the MOSFET SU and secondly to the source terminal S_{GD} of the transistor GD. The potential of the source terminal S_{GD} floats relative to the source potential of the MOSFETs M and SU.

10
15
20
25

In practice, a capacitor 21 will be connected between the source contact S of the MOSFET M and the source contact S_{SU} of the MOSFET SU, as is indicated by broken lines in Fig. 1. By virtue of the capacitive coupling of the two source terminals, when a specific threshold voltage is exceeded between the drain terminal D and the source terminal S, the parasitic transistor GD is able to turn on the MOSFET SU, which could then drive for example a control IC (see Figs. 4-5) with a low voltage potential in comparison with the load terminals, which, for its part, could be connected to the gate G of the MOSFET for driving purposes. The magnitude of the threshold voltage at which the semiconductor switch SU is turned on can be fixed by technological measures (implantation dose, gate oxide thickness).

Fig. 2 shows a cross section through the vertical semiconductor component according to the invention. The semiconductor component 20 has a substrate 1 having a first side I and a second side II, which substrate is n-conducting in the present example. A highly doped region of the same conductivity type is disposed on the second side II, which region constitutes the drain region 2. A metallization layer is applied on the drain region 2, on the side remote from the substrate 1, which metallization layer constitutes a drain contact 3.

A multiplicity of MOS cells M is provided on the first side I of the substrate 1, only two MOS cells M being illustrated in a manner representative of the multiplicity. In this case, a MOS cell M has a first well 4 of a conduction type, p in the present case, opposite to the substrate, which first well 4 is introduced into the substrate 1 and reaches to the first side I. A first source region 5, which is n-conducting, is introduced in the p-type well 4. This source region 5 reaches to the first side I of the substrate 1.

An insulating layer 8 is applied on the first side I of the substrate 1. This insulating layer 8 is perforated at the locations of the first source regions 5 of the MOS cells M, so that the first source region 5 is electrically conductively connected to a first source contact 6. A first gate 7 is applied on the insulating layer 8, which first gate 7 partly

covers the p-type well 4 and is likewise connected via a metallic gate contact (not shown).

Further MOS cells SU are provided in the substrate 1, in a manner isolated from the MOS cells M by a lateral

5 insulation 8. The further MOS cells, so-called start-up cells SU, are in this case constructed in exactly the same way as the MOS cells M. This means that a p-type well 4' is incorporated into the substrate 1, into which well, for its part, a source region 5' is incorporated, which reaches to the first side I. The source region 5' is electrically connected to a second source contact 6' reaching through the insulating layer 8. The first and the second source contact 6, 6' are not electrically connected to one another. The same applies to the corresponding gate contacts (not shown).

15 A second gate 7' is situated on the insulating layer 8 and at least partly covers the p-type well 4'. Furthermore, the gate 7' partly covers a source region 11 which, together with the p-type well 4' and the substrate 1, forms a parasitic pnp transistor. The latter is referred to as a "gate-drive cell" GD. The gate-drive cells GD are electrically connected to the gate 7'. The electrical connection to the gate 7' can be made, for example, via a metallic contact-connection 10.

In order to ensure that the start-up cells SU are turned on when a threshold voltage is exceeded between the drain

contact 3 and the first source contact 6 of the semiconductor component, the p-type region 11 is configured in such a way that the charge situated therein suffices to bring the second gate 7' to a sufficiently high potential. Therefore, provided 5 below the p-type region 11 lies a further region 11' of the same conductivity type, which is electrically readily conductively connected to the p-type region 11.

Fig. 3 illustrates the preferred configuration of the p-type regions 11, 11', that is to say the p-type region 11' extends 10 orthogonally from the first side I to the second side II of the semiconductor component. In order to increase the current-carrying capacity before or during breakdown and also to achieve a high avalanche strength of the MOS cells M, a p-type region 12 formed orthogonally to the first side I is 15 likewise provided below the p-type wells 4. The same likewise applies to the start-up cells SU, in which there is a buried p-type region 12' below the second p-type well 4'.

In Fig. 3, the buried p-type region 11 is surrounded by (in cross section) two start-up cells SU. It would also be 20 conceivable for a start-up cell SU to be surrounded by buried p-type regions 11.

Furthermore, Fig. 3 illustrates a "surge detection cell" SD, which, in principle, is constructed in a similar manner to a gate-drive cell GD. The surge detection cell SD also has a

buried p-type region 13 below its p-type region SD, but the p-type region 13, compared with the p-type regions 12 of the MOS cells M, is formed to a lesser extent in the direction of the second side. As a result, the surge detection cell SD has a
5 reduced breakdown voltage compared with the MOS cell M. It can then be used as overvoltage detection in the case of wiring with an external resistor. Furthermore, in the case of suitable wiring with the start-up cells, active zener protection of the semiconductor component is possible.

10 Furthermore, the surge detection cell SD is laterally insulated from the start-up cells SU.

15 If the highly doped n⁺-type layer 2 is replaced by a p -type layer, then the semiconductor component is embodied as an IGBT, whereas a MOSFET forms the basic structure in the present drawing.

Fig. 3 shows one possible configuration of the different cell types of the semiconductor component according to the invention in a plan view. In the present case, the gate-drive cells GD are surrounded exclusively by start-up cells SU.

20 However, it would also be conceivable for a plurality of start-up cells to be surrounded exclusively by gate-drive cells. This configuration is, for its part, in turn surrounded by a lateral insulation, which is in turn surrounded by MOS cells M. The layout of the individual cells
25 can be effected in a known manner in this case. A strip

layout is possible; the cells can have a circular cross section and occupy a hexagonal area packing or, in the case of a circular cross section, occupy an approximately square area packing or have a strip-shaped cross section. The same
5 applies to the configuration of the start-up cells and the gate-drive cells.

Fig. 4 shows an electrical equivalent circuit diagram for the semiconductor component according to the invention that is known from Fig. 3. Fig. 4 reveals the physical method of
10 operation particularly well. The semiconductor component 20 according to the invention has a MOSFET M including a multiplicity of MOS cells that are connected in parallel and form the active cell array. On the drain side, the MOSFET M is connected to the drain terminal of a further MOSFET SU. On
15 the source side, the MOSFET SU is connected via an integrated circuit IC to the gate G of the MOSFET M. It would also be conceivable for the source terminal of the MOSFET SU to be directly connected to the gate of the MOSFET M. Capacitance C2 represents the gate-source capacitance of the MOSFET SU. A
20 further capacitance C1 is connected up between the gate and the drain terminal of the MOSFET SU. This capacitance represents the charge present in the buried p-type region 11, 11' (space charge zone capacitance). Furthermore, a diode D1 is connected in parallel with the capacitance C1, the anode
25 terminal of the diode being connected to the gate of the MOSFET SU, while the cathode terminal is connected to the

drain terminal D. Two zener diodes ZD1, ZD2 are reverse-connected in series between the gate and the source of the MOSFET SU. This means that the anode terminal of the zener diode ZD1 is connected to the gate of the MOSFET SU, the cathode terminals of the zener diodes ZD1, ZD2 are connected to one another, while the anode terminal of the zener diode ZD2 is connected to the source S_{SU} of the MOSFET SU. The capacitance C1, the diode D1, and the two zener diodes ZD1, ZD2 form the gate-drive cell GD. Furthermore, the gate of the MOSFET SU represents the "source terminal S_{GD} " of the gate-drive cell GD. Moreover, an external charge store 21 connected up between the source terminals, the MOSFETs SU, M, is represented by broken lines in Fig. 4.

The diode D1 represents the junction between the buried p-type region 11, 11' and the substrate 1. The zener diodes ZD1, ZD2 reverse-connected in series form the parasitic transistor between the buried p-type region 11, the substrate 1 and the p-type well 4' of the start-up cell SU. The spacing between the start-up cell and the buried p-type region 11, 11' is such that the two zener diodes ZD1, ZD2 ideally have a reverse voltage of approximately 8 volts. The dimensioning of ZD1, ZD2 should ideally be identical. The threshold voltage of the MOSFET SU should be approximately 4 to 5 volts. The turning-on of the MOSFET M by application of a high voltage between the drain and source terminals can be explained as follows: the gate-drive cell GD serves as control electrode for the

MOSFET SU. This means that no current flows in the gate-drive GD itself; a current for charging the gate of the MOSFET SU is provided only on application of a high voltage between the drain and source terminals. The capacitance C1 forms a

5 voltage divider together with the zener diodes ZD1, ZD2 reverse-connected in series. On application of the high voltage between the drain terminal D and the source terminal S, the potential at the center tap of the voltage divider begins to rise. The charge that is stored in the capacitance C1 and is provided from the buried region 11, 11' begins to charge the gate-source capacitance C2 of the MOSFET SU. This causes the MOSFET SU to turn on; a current can flow to the source terminal S_{SU} of the MOSFET SU. Due to the external capacitance 21, the potential at the source terminal S_{SU} begins to rise. The zener diode ZD2 then performs a voltage-limiting function, i.e. the voltage between the gate terminal and the source terminal of the MOSFET SU is held at a value of approximately 8 volts. This value can be set by the dimensioning of the zener diodes ZD1, ZD2. Due to this
10
15
20 permanent potential difference, the MOSFET SU remains in the on state.

The capacitance 21 is dimensioned in such a way that the voltage value present at the source terminal S_{SU} reaches a magnitude that can drive the integrated circuit IC. The
25 latter can then drive the gate of the MOSFET M, and turn the latter on, in a suitable manner.

The MOSFET M is switched off only when the MOSFET SU is in an off state. For this purpose, on one hand, it is conceivable for the source terminal S_{SU} to be short-circuited with the source terminal S of the MOSFET M. On the other hand, it
5 would also be conceivable for the source terminal S_{SU} to be connected to the source terminal S_{GD} , so that the capacitance C2 could be discharged.

The diode D1 simultaneously represents a surge detection cell SD. Active zener protection of the MOSFET M is possible by
10 suitable dimensioning, which is determined either by the doping or, alternatively, the depth of the buried region 13'. The breakdown voltage of the diode D1, which then acts as a zener diode, must be set in such a way that it is smaller than
15 the breakdown voltage of the MOSFET M. If the breakdown voltage of the diode D1 is exceeded, then it supplies a charging current for the gate of the MOSFET S_{SU} , which is turned on in the manner described, and in this way turns the MOSFET M on. Destruction of the MOSFET M can thereby be prevented.

20 As already mentioned in the introductory part, it is also conceivable, given suitable dimensioning of all the components shown, for the gate of the MOSFET M to be directly connected to the source terminal of the MOSFET SU.

Fig. 5 shows an extension of the equivalent circuit diagram from Fig. 4. Fig. 5 illustrates cascading of the start-up cells. If, by way of example, the gates of ten start-up cells SU are charged by the capacitance C1, then the current

5 generated at the source terminal S_{SU} can be used to drive the gate of in each case a further ten start-up cells $S_{SU'}$. In total, then, 100 start-up cells $S_{SU'}$ are in the on state, which can in turn each turn on ten further start-up cells $S_{SU''}$.

1000 start-up cells $S_{SU''}$ are then available which can charge the external capacitance 21. This simple cascading makes it possible also to drive a large active cell array (MOSFET M).

In the example described, it was assumed that a start-up cell SU was able to turn on ten further cells. In accordance with the number of cascading stages, any desired charge can be generated which suffices to turn on a MOSFET M.

Fig. 6 illustrates a plan view of a cell array cascaded in this way. A buried p-type region 11 is electrically connected to two adjacent gates 6'. The gates 6' turn on the adjacent start-up cells SU that, on the source side, are electrically connected to further gates 6''. The gates 6'' can be used to turn on a further twelve start-up cells $S_{U'}$, which can then be connected, for example, directly to the gate of the MOSFET M.

In the case of cascading the start-up cells care must be taken to ensure that the gate metallization layer of each cascade can be contact-connected externally. In order to switch the

MOSFET M off, each individual cascading stage must be switched off, so that a charge "remains" in none of the start-up cells.

In Fig. 7, the cells illustrated have a square layout. It is also conceivable, of course, for the cells to be of circular or hexagonal construction.

Fig. 7 shows a cross section through a laterally constructed semiconductor component. On the left-hand side, Fig. 7 shows the MOS cells M constructed in a known manner. In the same way as in the case of the vertically constructed semiconductor component, the start-up cells S1 are provided with a dedicated, second source contact. This second source contact 6' is electrically insulated from the first source contact 6 of the MOS cells M. The mutual insulation of the cells is realized by a lateral insulation 9. The gate-drive cell GD is embodied as a parasitic transistor between the buried p-type region 11, the substrate 1 and the p-type well 4', the charge required for charging the second gate 7' being present in the buried p-type regions 11, 11'. The buried p-type region 11' extends from the p-type region 11 in the direction of the drain 3 along the first side I of the substrate 1. The buried p-type region 11' is in good electrical contact with the p-type region 11. Furthermore, it now goes without saying that the p-type region 11 is electrically connected to the second gate 7'.

The present semiconductor component makes it possible to generate a signal from a high load voltage at the load terminals of a MOSFET or IGBT, which signal is suitable for driving a control IC or directly the control electrode of the semiconductor component.

5

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
22